

METHOD AND APPARATUS FOR DELIVERING
POWER TO HIGH PERFORMANCE ELECTRONIC ASSEMBLIES

CROSS-REFERENCE TO RELATED APPLICATIONS

5 This application claims benefit of the following U.S. Provisional Patent Applications, each of which are incorporated by reference herein:

Application Serial No. 60/187,777, entitled "NEXT GENERATION PACKAGING FOR EMI CONTAINMENT, POWER DELIVERY, AND THERMAL DISSIPATION USING INTER-CIRCUIT ENCAPSULATED PACKAGING TECHNOLOGY," by Joseph T. DiBene II and David H. Hartke, filed March 8, 2000;

10 Application Serial No. 60/196,059, entitled "EMI FRAME WITH POWER FEED-THROUGHS AND THERMAL INTERFACE MATERIAL IN AN AGGREGATE DIAMOND MIXTURE," by Joseph T. DiBene II and David H. Hartke, filed April 10, 2000;

15 Application Serial No. 60/219,813, entitled "HIGH CURRENT MICROPROCESSOR POWER DELIVERY SYSTEMS," by Joseph T. DiBene II, filed July 21, 2000;

Dis B1 Application Serial No. 60/232,971, entitled "INTEGRATED POWER DISTRIBUTION AND SEMICONDUCTOR PACKAGE," by Joseph T. DiBene II and James J. Hjerpe, filed September 14, 2000;

20 Application Serial No. 60/251,222, entitled "INTEGRATED POWER DELIVERY WITH FLEX CIRCUIT INTERCONNECTION FOR HIGH DENSITY POWER CIRCUITS FOR INTEGRATED CIRCUITS AND SYSTEMS," by Joseph T. DiBene II and David H. Hartke, filed December 4, 2000;

Dis B2 Application Serial No. 60/251,223, entitled "MICRO-I-PAK FOR POWER DELIVERY TO MICROELECTRONICS," by Joseph T. DiBene II and Carl E. Hoge, filed December 4, 2000, and

Dis B3 Application Serial No. 60/251,184, entitled "MICROPROCESSOR INTEGRATED PACKAGING," by Joseph T. DiBene II, filed December 4, 2000.

Dis B4 30 This patent application is also continuation-in-part of the following co-pending and commonly assigned patent applications, each of which applications are hereby incorporated by reference herein:

Application Serial No. 09/353,428, entitled "INTER-CIRCUIT ENCAPSULATED PACKAGING," by Joseph T. DiBene II and David H. Hartke, filed July 15, 1999;

5 Application Serial No. 09/432,878, entitled "INTER-CIRCUIT ENCAPSULATED PACKAGING FOR POWER DELIVERY," by Joseph T. DiBene II and David H. Hartke, filed November 2, 1999;

Application Serial No. 09/727,016, entitled "EMI CONTAINMENT USING INTER-CIRCUIT ENCAPSULATED PACKAGING TECHNOLOGY" by Joseph T. DiBene II and David Hartke, filed November 28, 2000;

10 Application Serial No. --/---,---, entitled "METHOD AND APPARATUS FOR PROVIDING POWER TO A MICROPROCESSOR WITH INTEGRATED THERMAL AND EMI MANAGEMENT," by Joseph T. DiBene II, David H. Hartke, James J. Hjerpe Kaskade, and Carl E. Hoge, filed February 16, 2001; and

15 Application Serial No. --/---,---, entitled "THERMAL/MECHANICAL SPRINGBEAM MECHANISM FOR HEAT TRANSFER FROM HEAT SOURCE TO HEAT DISSIPATING DEVICE," by Joseph T. DiBene II, David H. Hartke, Wendell C. Johnson, and Edward J. Derian, filed March 2, 2001.

20 This patent application is also related to Application Serial No. --/---,---, entitled "METHOD AND APPARATUS FOR THERMAL AND MECHANICAL MANAGEMENT OF A POWER REGULATOR MODULE AND MICROPROCESSOR IN CONTACT WITH A THERMALLY CONDUCTING PLATE," by Joseph T. DiBene II and David H. Hartke, filed on same date herewith, which application is hereby incorporated by reference herein.

BACKGROUND OF THE INVENTION

1. Field of the Invention

This invention relates in general to a system for providing electrical continuity between a plurality of circuit boards, and in particular to a method and apparatus for improving the packaging and distribution of power to high performance electronic circuit assemblies.

2. Description of the Related Art

As electronic circuitry becomes more complex, packaging of the circuitry has become more difficult. The common method for packaging integrated circuits (ICs) and other electronic components is to mount them on printed circuit boards (PCBs) or other substrates such as ceramics having alternating conductive and non-conductive layers or planes sandwiched or bonded together to form a dense X-Y signal interconnect. For a number of years, the operating voltage of ICs was approximately 5 volts and the power consumption was generally less than 1 watt. This relatively high supply voltage and low power level allowed the packaging of a large number of ICs on a single PCB with power distribution incorporated into one or more of the PCB planes.

More recently advances in silicon fabrication techniques have permitted the manufacture of high performance IC packages with operating voltages at or below 1 volt and power levels in excess of 100 watts. As described in co-pending and commonly assigned patent application serial number --/---,---, METHOD AND APPARATUS FOR PROVIDING POWER TO A MICROPROCESSOR WITH INTEGRATED THERMAL AND EMI MANAGEMENT, by Joseph T. DiBene II, David H. Hartke, James J. Hjerpe Kaskade, and Carl E. Hoge, filed February 16, 2001, which application is hereby incorporated by reference, the transient current to some of these packages can exceed hundreds of amps per microsecond. To assure optimum performance under these conditions, it is important that the electrical path from the power supply to the IC be designed to accommodate high current flow and low series inductance, two goals which are difficult to achieve at the same time. The present invention achieves both of these

goals, while also allowing for a compact, integrated stack-up system design that permits thermal dissipation and control of electromagnetic interference (EMI).

SUMMARY OF THE INVENTION

5 To address the requirements described above, the present invention discloses a method, apparatus, article of manufacture, for providing power from a first circuit board having a first circuit board first conductive surface and a first circuit board second conductive surface to a second circuit board having a second circuit board first conductive surface and a second circuit board second conductive surface. The apparatus
10 comprises a first conductive member, including a first end having a first conductive member surface electrically coupleable to the first circuit board first conductive surface and a second end distal from the first end having a first conductive member second surface electrically coupleable to the second circuit board first surface. The apparatus also comprises a second conductive member, having a second conductive member first surface electrically coupleable to the first circuit board second surface and a second
15 conductive member second surface distal from the second conductive member first surface electrically coupleable to the second circuit board second conductive surface. In one embodiment of the invention, the second conductive member is hollow, and is disposed within the second conductive member in a coaxial arrangement. If desired, a dielectric can be placed between the first conductive member and the second conductive member. The dielectric, or the dimensions of the first conductive member and the second conductive member can be defined so that the apparatus exhibits an impedance that can be used cooperatively with circuit elements on either the first circuit board or the second circuit board. One of the advantages of the present invention is the integration of function
20 in which the apparatus operates both as a rigid standoff to separate the first circuit board from the second circuit board, and a conduit for delivering power and a ground return (or other signals) between the circuit boards as well. While the apparatus will be discussed in terms of providing a power signal from a first circuit board to a second circuit board, it can also be used to provide power to a plurality of circuit boards in a stacked up
25 configuration, all with minimal impedance.
30

BRIEF DESCRIPTION OF THE DRAWINGS

Referring now to the drawings in which like reference numbers represent corresponding parts throughout:

5 FIG. 1A is a two-dimensional section view illustrating an architecture in which the present invention may be usefully employed in delivering power to a microprocessor;

FIG. 1B is a section view of a microprocessor package used in FIG. 1A which further illustrates the location of the power standoff assemblies associated with delivering power to the microprocessor shown in FIG. 1A;

10 FIG. 2A is a two-dimensional section view of a conceptual coaxial interconnect illustrating the delivery of electrical energy from an upper planar circuit structure to a lower planar circuit structure;

FIG. 2B is two-dimensional plan view of the current flow to the coaxial interconnect structure in the upper planar circuit of FIG. 2A;

15 FIG. 3 is a two-dimensional section view of a power standoff assembly structure in which the inner cylinder is swaged to the upper planar circuit and a screw forms both a mechanical and electrical connection to a lower planar circuit;

FIG. 4 is a two-dimensional section view of a power standoff assembly structure in which the inner cylinder is swaged to the upper planar circuit and a crushable spring washer forms an electrical connection from the inner cylinder to a lower planar circuit while a screw forms the mechanical connection;

20 FIG. 5 is a two-dimensional section view of a power standoff assembly structure in which the inner cylinder is swaged to the upper planar circuit and a screw forms the mechanical connection of the inner cylinder to the lower circuit structure while a spring feature is incorporated into the outer cylinder in order to accommodate electrical connection of the outer cylinder to the lower planar circuit;

25 FIG. 6 is a two-dimensional section view of a power standoff assembly structure in which the inner cylinder is swaged to the upper planar circuit and a screw forms the mechanical connection of the inner cylinder to the lower circuit structure while a spring

insert is incorporated into the outer cylinder in order to accommodate electrical connection of the outer cylinder to the lower planar circuit;

FIG. 7A is a two-dimensional section view of a power standoff assembly structure in which the inner and outer cylinders are soldered to the upper planar circuit while the connection of these cylinders to the lower planar circuit is accommodated by the use of a coaxial spring contact assembly;

FIG. 7B is a two-dimensional plan section view of the power standoff assembly structure of FIG. 7A further illustrating the coaxial spring contact assembly;

FIG. 8A is a two-dimensional section view of a power standoff assembly structure in which coaxial ring structures are joined to both the upper and lower planar circuit to form coaxial blades which engages into spring furrows which are an integral part of the inner and outer cylinders of the power standoff assembly;

FIG. 8B is a two-dimensional plan view of the coaxial ring structure of FIG. 8A;

FIG. 8C is a two-dimensional plan view looking into the spring furrows of the inner and outer cylinders of FIG. 8A;

FIG. 9A is a two-dimensional section view of a planar circuit structure illustrating how the layers in a multi-layered circuit structure can be arranged to efficiently couple dynamic electrical current impulses from the inner planes of the planar structure to the inner and outer cylinders of a coaxial power standoff assembly utilizing a screw connection as illustrated in FIG. 3;

FIG. 9B is a two-dimensional plan view of the top most layer of FIG. 9A;

FIG. 9C is a two-dimensional plan view of the upper inner layer of FIG. 9A;

FIG. 9D is a two-dimensional plan view of the lower inner layer of FIG. 9A; and

FIG. 9E is a two-dimensional plan view of the lower most layer of FIG. 9A;

FIG. 10 is a 2-dimensional plan view of a power standoff assembly structure which is surrounded with capacitors in order to improve the overall connection impedance;

FIG. 11A is a 2-dimensional side view of an EMI frame using power standoff assemblies integral with the frame assembly;

FIG. 11B is a 2-dimensional plan section view of the EMI frame shown in FIG. 10A; and

FIG. 12 is a diagram illustrating how the power standoff assembly can be used as a circuit element between the circuit boards.

5

DETAILED DESCRIPTION OF PREFERRED EMBODIMENTS

In the following description, reference is made to the accompanying drawings which form a part hereof, and which is shown, by way of illustration, several embodiments of the present invention. It is understood that other embodiments may be utilized and structural changes may be made without departing from the scope of the present invention.

10

Overview

The present invention discloses an apparatus for providing power from a first circuit board to a second circuit board. In one embodiment, the apparatus (hereinafter alternatively referred to as a POWERDIRECT or a standoff) comprises an inner cylindrical cylinder, an intermediate coaxially located insulator or dielectric material and an outer coaxially located cylindrical cylinder. The standoff is disposed between a first planar structure or printed circuit board and a second planar structure or printed circuit board to provide a path for the transfer of electrical power and a ground return between the two planar structures in an efficient manner. This creates a very low impedance interconnect between power and groundplanes on the first planar structure and power and ground planes on the second planar structure.

15

20

The present invention discloses a variety of methods in which the coaxial cylinders of the power standoff assembly may be joined to the upper and lower planar structures and their internal power planes. It also discloses efficient methods of connecting the internal power planes of the planar structures to external land features of the planar structures in such a manner as to further enhance the efficacy of the interconnect between power planes on the first planar structure and power planes on the second planar structure.

25

30

The present invention further describes a specific application where the power standoff assembly may be especially beneficial to delivering power to high performance microprocessor packages in such a manner as to negate the need to integrate power regulation circuitry directly onto the microprocessor package (On-Package-Voltage-Regulation, OPVR) so as to improve the producibility, yield and cost of modern high performance microprocessors.

Encapsulated Circuit Assembly

Typically, a modern high performance microprocessor die is flip-chip attached to an organic or ceramic substrate utilizing a Controlled-Collapse-Chip-Connection (C4). The substrate has one or more power planes which are used to distribute power to the chip connections. Often the power requirements of the microprocessor exceed 100 watts at operating voltages of approximately 1 volt and transient current requirements in excess of 100 amps per microsecond. Typically power conditioning may be provided by a voltage regulation module (VRM). The stringent power demands require that the VRM be very closely coupled to the microprocessor or directly mounted on to the microprocessor substrate. OPVR architectures combine VRM technology with high performance silicon technology all on a common substrate. The OPVR often very expensive because of the very large number of layers required to manage both the power and signal interconnect to the microprocessor die. The resulting assembly also has reduced yield and higher costs than what might be achieved if the microprocessor function could be separated from the VRM function.

FIG. 1A is a diagram illustrating a stack up assembly 100 illustrating the use of a power standoff assembly 105 to deliver power to a microprocessor substrate 101 and its associated lid 108 from a remotely located VRM assembly 102. In the illustrated embodiment, the VRM assembly 102 surrounds the microprocessor lid 108, thus saving space in the z (vertical) axis.

The microprocessor lid 108 is thermally coupled to a heatsink structure 106 through a thermal coupling mesa 107 and appropriate thermal interface material (TIM) such as thermal grease (not shown) which can be integral to the base of 107 or a separate

structure that is coupled (i.e. bonded, or metallically fused) to the base of the heatsink structure 106. Furthermore, heat generated from components in the VRM assembly 102 can be thermally attached directly to the base of heatsink assembly 106, thus sharing the heat dissipation benefits of the heatsink assembly 106. Signals from the microprocessor
5 can be connected through pins (not shown) to socket 104 which is mounted to main board 103.

Power from the VRM assembly 102 is efficiently coupled to the microprocessor substrate 101 by utilizing one or more power standoff assemblies 105. In one embodiment, four power standoff assemblies 105 are used, and each is located proximate
10 a corner of the microprocessor substrate 101.

FIG. 1B is a diagram showing the location of the four power standoff assemblies 105 proximate the corners of the microprocessor substrate 101. The power standoff assemblies 105 may be located in other locations on the substrate 101 such as at the center of each side. Further, the number of power standoff assemblies 105 used can be
15 varied to meet the power needs of target microprocessor or other high performance Integrated Circuit assembly.

Coaxial Interconnect

FIGs. 2A and 2B are diagrams illustrating transfer of energy from a source (such as a VRM assembly 102) on a first circuit board 201 to a second circuit board 202
20 through one or more power standoff assemblies 105.

A power signal 211 supplying current flows from the VRM on the first circuit board 201 (hereinafter alternatively referred to as first PCB) through a conductive plane 204 in or on the first circuit board 201 to one or more power standoff assembly
25 connections 105D. The power signal 211 then passes through the first conductive member 105A to similar connections on the second circuit board 202 and then onto a conductive plane 207 in or on the second circuit board 202, and thence to the load (e.g. the IC, microprocessor or other power dissipating device). A ground return signal 212 passes from a ground plane 206 in or on the second circuit board 202 through a
30 conductive surface 213 to a second conductive member 105B, through the second

conductive member 105B, to a conductive plane 205 on or in the first circuit board 201. This acts as a ground return for the VRM power signal 211. The space between the first conductive member 105A and the second conductive member 105B may include a dielectric or electric insulator 105C, if desired.

- 5 In a preferred embodiment, the second conductive member 105B is hollow and the first conductive member 105A is disposed within the second conductive member 105B such that they are substantially coaxial (e.g. the major axis of the first conductive member and the major axis of the second conductive member are co-linear). In this embodiment, the series inductance of the power standoff assembly 105 is governed
- 10 primarily by the basic equation;

$$L_{COAX} = \frac{\mu_0 h}{2\pi} \ln(D_o / D_i)$$

- where μ_0 is the permeability of space, h is the length of the power standoff 105 body, D_o is the inner diameter of the outer conductor, and D_i is the diameter of the inner conductor.
- 15 As the diameters get closer to each other the natural log function approaches zero. This is the theoretical limit the inductance may achieve with such a construction. Practical issues limit achieving this limit however with such a construction the actual inductance achieved may be very low.

- As described further with respect to FIGs. 9A-9E, the power plane 204, 206 and
- 20 the ground plane 205, 207 of the first circuit board 201 and the second circuit board 202 may be on inner layers, instead of on an external surface of the circuit boards 201, 202. In this case, through holes can be used on the first circuit board 201 and second circuit board 202. These thru-hole patterns can also be coaxially arranged proximate to where first and second conductive members 105A, 105B are connected to the first and the
- 25 second circuit boards 201, 202. Also, plane inductance (inductance from the plane pairs 204/205 and 206/207) can be reduced by the bringing the plane pairs 204/205 and 206/207 closer together.

One of the reasons for reducing the interconnection inductance is that the voltage drop across the interconnect is crucial for proper operation. As stated previously, high

current slew-rates can create large drops across an inductive interconnect. This may be seen by the simple equation for the dynamic voltage drop across an interconnect:

$$\Delta V \cong I_{STEP} R_{AC} + L_{TOT} \frac{dI}{dt}$$

- 5 Where I_{step} is the step current the IC creates when switching transistors internally, R_{AC} is the AC resistance of the interconnect, L_{TOT} is the total inductance of the interconnect, and dI/dt is the rate of change or AC current slew-rate which occurs due to the switching transistors. Often the inductance is the dominant element in the path and thus contributes to the largest portion of the drop across the interconnect.

10

Coaxial and Multi-Axial Embodiments

FIG. 3 is a diagram illustrating a preferred embodiment of a power feed standoff assembly 300. The power feed standoff assembly 300 is used to route power and/or signals from a first circuit board 306 to a second circuit board 309.

- 15 The power feed standoff assembly 300 comprises a first conductive member 303 and a second conductive member 301. In the illustrated embodiment, the second conductive member 301 is hollow, and the first conductive member 303 is disposed within the second conductive member 301. Also, the first conductive member 303 and second conductive member 301 are coaxial (e.g. the longitudinal axes of symmetry of each are substantially colinear). Hence, the first conductive member 303 is disposed within and coaxially with the second conductive member 301.

- 20 The first conductive member 303 includes a first end 314. The first end 314 includes a shoulder portion 316 having a first conductive member first surface 313 that is electrically coupleable to a first conductive surface 307 on the first circuit board 306, such as a pad. The first conductive member 303 also includes a second end 315 distal from the first end 314 having a first conductive member second surface 317 electrically coupleable with a first conductive surface 310 or pad of the second circuit board 309. In the illustrated embodiment, the first conductive member second surface 317 does not directly contact the first surface 310A of the second circuit board 309. Instead, electrical coupling

between the first conductive member second surface 317 and the first surface 310 of the second circuit board 309 is accomplished by a screw 305 that is electrically coupled to both the first conductive member 303 and the first surface 310 of the second circuit board. As can be seen from FIG. 3, direct contact between the second end 315 of the first
5 conductive member and the first surface 310 of the second circuit board 309, (e.g. between first conductive member second surface 317 and surface 310A) is possible as well.

The second conductive member 301 includes a first end 318 having a second conductive member first surface 319. The second conductive member first surface 319 is
10 electrically coupled to a first circuit board 306 second conductive surface 308. In the illustrated embodiment, the second conductive member first surface 319 is directly coupled to the first circuit board 306 second conductive surface 308, but this need not be the case.

The second conductive member 301 includes a second end 320 having a second conductive member second surface 321. The second conductive member second surface 321 is electrically coupled to the second circuit board second surface 311. In the
15 illustrated embodiment, the second conductive member second surface 321 is directly coupled to the second circuit board second surface 311, but this need not be the case.

In the illustrated embodiment, both the first conductive member 303 and the second conductive member 301 are cylindrical in shape (e.g. generally circular in cross section), but this need not be the case. Although the circular cross section depicted is preferred, the first and second conductive members 303, 301 may be of an ovoid, rectangular, or trapezoidal cross section. Or, the conductive members 301, 301 may simply be a pair of adjacent linear conductive members having an insulator or insulating space therebetween. In each case, the longitudinal axes of symmetry for the first and
20 second conductive members 301, 303 can be made substantially co-linear.

The first conductive member 303 is also disposed through a plated through hole (PTH) in the first circuit board 306. The inner conductive member 303 can be affixed to the first circuit board 306 by a swage 312. The swage 312 works cooperatively with the shelf portion 316 to affix the first conductive member 303 to the first circuit board 306.

FIG. 3

Sub
C5

25

Sub
C30

Sub 7
The inner conductive member 303 can be further attached to the first circuit board 306 by a soldering. However, soldering alone is not the preferred method of affixing the first conductive member 303 to the first circuit board 306.

Sub 7
C8
The plated through hole 322 and the surrounding first circuit board first surface 307 together with the first conductive member 303 define an inner coaxial power circuit. In one embodiment, the inner coaxial power circuit is completed by a conductive fastening device 305 such as a screw, which makes electrical contact with the first conductive member 303 and the second circuit board first surface 310, thus forming an electrically conductive path from the first circuit board 306 to the second circuit board 309. In one embodiment, the inner conductive member 303 includes hollow portion having a threaded inner surface configured to accept and hold. Also, the height of the first conductive member 303 is typically slightly less than the height of the second conductive member 301 for the reasons described below.

Sub 7
C9
The second conductive member 301 forms the outer coaxial circuit engaging the first circuit board second surface 308 (which may include a power pad pattern) and the second circuit board second surface 311. In one embodiment, dielectric 302 does not grip the first conductive member 303 and the second conductive member 310 so tightly that their relative position can not be adjusted slightly with a force imparted by fastener 305 such that the upper surface 313 of outer conductor 305 can come into intimate contact with the first circuit board second surface 308, thus completing the upper half of the outer coaxial power circuit.

Sub 7
C10
Because the inner conductor 303 is slightly shorter than outer conductor 301 both circuit feeds have identical and predictable joining forces between PCB 306 and PCB 309. Such would not be the case if the two conductors 303, 301 were of approximately equal length where slight variations in length may cause an unpredictable shift in forces between the two conductors as they press against the surfaces of PCB 306 and 309. Further, the fact that the first conductive member 303 and the second conductive member 301 are coaxially arranged to reduce the unwanted electromagnetic fields that might be created from electric disturbances induced into the assembly 300.

Production

5 The power feed standoff assembly 300 may be produced by separately fabricating items 301, 302 and 303 and pressing them together forming an inseparable assembly. The power feed standoff assembly 300 may also be produced by separately fashioning the inner conductive member 303 and the outer conductive member 301, supporting the members 301, 303 in a fixture, and inserting a dielectric 302 into the gap separating 301 and 303 (e.g. under heat and pressure) and curing the dielectric material 302. It should be noted that outer conductor 301, dielectric 302 and inner conductor 303 can be separate parts that are assembled in a different sequence than is described above without detracting from the benefits of this invention.

10

Further Embodiments

FIG. 4 is a two-dimensional sectional view of another embodiment of the power feed standoff assembly 300. This embodiment is similar to that which is depicted in FIG. 3, however, a compressible conductive member such as a crushable washer 401 is disposed between the second circuit board 309 first surface 310 and the second conductive member second surface 317. This provides a direct path by which current in the first conductive member 303 passes directly to the first conductive surface 310 on the second circuit board 309. Crushable washer 401 significantly reduces the inductance of the electrical interconnect because current does not have to proceed through the screw body to the second circuit board 309 first conductive surface 310 but rather can proceed directly from the base of first conductive member 303 to the second circuit board 309 first conductive surface 310. The crushable washer 401 still provides the benefits of providing predictable forces to both the first and second conductive members 303 and 301 respectively. It is also noted that the compressible range of crushable washer 401 need not be excessive, since acceptable tolerances are limited principally to the height variations between first conductive member 303 and second conductive member 301 which is typically less than 2 mils.

15

20

25

FIG. 5 is a two-dimensional section view of another embodiment of the power feed standoff assembly 300, illustrating still another structure for eliminating the passage

of current through the screw 305. Unlike the embodiment FIG. 4 where the compliant member was the crushable washer 401 located so as to be in electrical contact with the first conductive member 303, in this embodiment, the outer conductive member 302 is fabricated with a compressibly compliant section 501 which acts as a spring. In this arrangement, first conductive member 303 is the "fixed" height member and second conductive member 301 is the slightly longer member with a compressibly compliant end section 501 that takes up variations in height between first conductive member 301 and the second conductive member 303, providing a direct path for both the inner and outer conductor members 303 and 301 to the second circuit board first conductive surface 310 and the second circuit board second conductive surface 311, respectively.

FIG. 6 is a diagram of another embodiment of the power feed standoff assembly 300. In this embodiment, the integral compressibly compliant end section formed by the body of the second conductive member 301 is replaced with a separate compressibly compliant member 601 which is inserted into an inner surface of the second conductive member 301.

FIG. 7A is a diagram illustrating another embodiment of the power feed standoff assembly 300. In this embodiment, a spring contact assembly 702 is used to electrically connect lower half (i.e. the second ends) of the first conductive member 303 and the second conductive member 303 to the second circuit board 309. In the illustrated embodiment, the spring contact assembly 702 includes a plurality of cantilever beam spring elements 703 and 704.

In this embodiment, the upper portion (i.e. the first end) of the power feed standoff assembly 300 may be solder attached to the first circuit board 306 and the respective first circuit board conductive surfaces 307 and 308. This is because this embodiment does not result in a continuous vertical force on the power feed standoff assembly 300 causing solder creepage. A center locating feature 701 in or on the first circuit board 306 may be employed to locate the power feed standoff assembly 300 to the first circuit board 306 prior to soldering.

The spring contact assembly 702 comprises a first contact 703 that is electrically coupled to the second circuit board second conductive surface 311. The first contact 703 slidably and releaseably contacts the outer surface of the second conductive member 301. The spring contact assembly 702 further comprises a second contact 704 that is

5 electrically coupled to the second circuit board first conductive surface 310, and slidably and releasably contacts an inner surface of the first conductive member 303. An insulating member 705 is disposed between a portion of the first contact 703 adjacent to second conductive member second surface 710. The insulating member 705, which can be made from plastic, is used to hold together spring contacts 703 and 704 prior to

10 permanent installation onto second circuit board conductive surfaces 310 and 311, and to insulate the spring contact 703 from the second conductive surface 311. The spring contact assembly 702 is used to electrically contact the first and second conductive members 303, 301 of the power feed standoff assembly 300 in a low inductance manner to conductive surfaces 310 and 311 on the second circuit board 309. A center locating

15 feature 706 in or on the second circuit board 309 may be useful in locating the spring contact assembly 702 to the second circuit board 309 prior to soldering. The contacts 703, 704 of the spring assembly can be ring-shaped when viewed from above, or may comprises a plurality of piecewise linear springs disposed radially to contact the first and second conductive members 303, 301. This embodiment is further illustrated in FIG. 7B,

20 which presents a plan section view looking downward into the spring assembly 702.

FIG. 8A is an illustration of a further embodiment of the present invention in which the ends of the power feed standoff assembly 300 include a receptive spring assembly 805.

The receptive spring feature 805 includes a blade portion 801 and a spring portion

25 804 for slidably engaging the blade portion 801, thus making electrical contact between the blade portion 801 and the spring portion 804. In the illustrated embodiment, the spring portion 804 includes opposing spring portions 804A, 804B, which grasp the mating blade portion 801 (which, when viewed from below, have the appearance of concentric blades) therebetween. The male portion 801A of the blades 801 are mounted

30 to the respective circuit boards by an attachment portion 801B which has a surface

suitable for mounting on the conductive surfaces of the respective circuit boards (e.g. the first conductive member 303 electrically coupled to a first conductive surface 307 and the second conductive member 301 electrically coupled to the second conductive surface 308).

5 FIG. 8B is a plan view of the power feed standoff assembly 300 illustrated in FIG. 8A looking into the concentric blade assemblies 801 and 802. In order to ease the assembly of blade assemblies 801 and 802 to first and/or the second circuit boards 308, 309, blade assemblies 801 and 802 can be joined together with an insulative plastic resin 803, thus forming the integrated blade assembly 806. Although not shown, this assembly
10 may have vertical protrusion features that are a part of 801, 802 or 803 which engage into mating holes in PCBs 306 and 309 to facilitate alignment and assembly.

In order to improve the flexibility of female portion 804 of the receptive spring assembly, the female portion 804 can be segmented in a plurality of segments arranged in concentric rings.

15 FIG. 8C is a plan view looking into the top or bottom of the first and second conductive members 803 and 801 illustrating how the female portion 804 can be segmented.

20 In usage, power feed standoff assembly 300 is simply plugged into assembly 806 without the need for a fastener. It will be recognized that power feed standoff assembly 300 need only have spring arrangement 804 and blade assembly 801, 802 on one side, and that the other side of the assembly 300 can be permanently secured to either PCB 306 or 309 using methods previously described in this invention disclosure. Further although in the illustrated embodiment, the receptive spring assembly 804 is included on both the first conductive member 303 and the second conductive member 301, this assembly can
25 be utilized on only one of the conductive members, or a single-sided spring (e.g. excluding 804B) can also be used if desired. Further, the receptive spring assembly 805 can be an integral part of the first and or second conductive members 303, 301, or can be separately fashioned, and affixed to the ends of the first and second conductive members 303, 301.

In order to improve the benefit of the power feed standoff assembly 300, it is beneficial to efficiently couple the electrical energy from the conductive surfaces of the first and second circuit boards 306, 309 to the first and second conductive members 303, 301.

5 The preceding discussion described the circuit board conductive surfaces (pad) features as simply a power pad which connect to either the first or second conductive members 303, 301. In many cases, the power and ground planes of the first and second circuit boards 306, 309 are not disposed on an outer surface of the circuit board, but rather, are disposed in inner layers, separated by one or more insulative layers. Such low
10 impedance power planes within the PCBs 306, 309 can be coupled to the first conductive member 303 and the second conductive member 301 as described below.

FIG. 9A is a drawing presenting a section view of an exemplary circuit board 900 (or PCB) that could be in place of the first circuit board 306 and or the second circuit board 309.

15 Generally, PCB 900 will have at least one pair of conductive planes dedicated to power distribution. FIG. 9A, for example, illustrates a first conductive plane 902 and a second conductive plane 903. Conductive plane 902 can be considered the voltage power plane and plane 903 can be considered the ground power plane, which together represent a power plane pair. These planes are usually separated from each other by a thin
20 dielectric or insulative layer 950 to keep the electrical impedance of the power plane pair low.

To electrically connect the conductive planes to the first and second conductive members 303, 301 of the power feed standoff assembly 300, it is desirable to bring the electrical energy from the power plane 902 and the ground plane 903 to external surface
25 features of the PCB 900. This can be accomplished by a first plurality of plated through holes 906 to provide an electrical path from the power plane 902 to one or more conductive surfaces 910, 911 on the external surface of the circuit board 900, and a second plurality of plated through holes 905 to provide an electrical path from the ground plane 903 to one or more other conductive surfaces 912, 956 of the circuit board 900. The
30 PTHs 906 and 905 are arranged so as to coincide with the location of the first conductive

member 303 and the second conductive member 301, respectively, when the power feed standoff assembly is disposed adjacent to the circuit board 900. When the circuit board 900 includes an aperture for a screw or other fastener, the PTHs 906 can be arranged in concentric circles (an inner concentric circle and an outer concentric circle) around the aperture as shown.

In FIG. 9A concentric PTHs 906 connect to voltage power plane 902 and surface plane pads 910 and 911 shown in FIGs. 9B and 9E. Additionally, main screw hole 907 electrically connects to voltage power plane 902 and conductive surface plane pads 910 and 911.

Collectively, the preceding creates one half of the low impedance connection from the power plane 902 to the surface pad 910. As described in the previous embodiments, the further connection to the power plane of the second circuit board can be accomplished as described in any of the foregoing embodiments. For example, through the first conductive member 303, the fastener 305, and the washer 304, and hence, to a power plane in the second circuit board as shown in FIG. 3.

Similarly, concentric ring of PTHs 905 connect to ground power plane 903 and to surface plane pads 912 and 956. Thus, when second conductive member 301 shown in FIG. 3 connects to surface pad 912, the second half of the low impedance connection from the power ground plane 903 to the second conductive member 301 is created.

FIG. 9C and 9D illustrate the conductive patterns for power planes 902 and 903 respectively. It will be understood that although they are shown as terminating, exterior conductive feature 951 in FIG. 9C and feature 953 in FIG. 9D extend out and represents a continuum of each of the power planes in PCB 309.

Note that the arrangement of external conductive surfaces 307, 308, 310, and 311 depicted in FIG. 3 is essentially duplicated in the embodiment shown in FIG. 9A. That is, with respect to the second circuit board 309, surfaces 910 and 911 are analogous to surfaces 307, and surface 912 is analogous to surface 311. And, with respect to the first circuit board 306, surfaces 910 and 911 are analogous to surface 307 and surface 956 is analogous to surface 308.

The foregoing describes exemplary embodiments of how internal power planes may be efficiently coupled to a screw terminal of FIG. 3. The techniques presented herein can be extended to a general case which a concentric ring of PTHs from the power planes join to surface features of the target PCB in order to efficiently couple the electrical energy of the planes into the concentric coaxial cylinders of the power standoff assembly.

FIG. 10 illustrates an arrangement where the power standoff assembly 300 is mounted on PCB 306 and is surrounded with surface mount bypass capacitors 1001. In practice when a power plane structure consisting of a voltage and ground plane, for example, is connected to a power standoff assembly 300 the concentration of the electromagnetic fields as they approach the power standoff assembly 300 tend to create an increasing impedance at the power standoff assembly 300 connection due to the fact that the current paths are utilizing an ever decreasing portion of the planar structure in which the power is passing. This effect can be reduced by adding bypass capacitors 1001 which are connected to power planes within PCB 306 in a concentric pattern as shown in FIG. 10 so as to reduce the impedance of the planes at a point very near to the power standoff assembly 300 connections to the plane. This arrangement is superior to placing bypass capacitors 1001 at a remote point from the power standoff assembly 300 where the impedance of the planes at the power standoff assembly 300 connection are not corrected.

FIG. 11A and 11B illustrate such an electromagnetic interference (EMI) frame 1101 incorporating power coupling devices therein. The EMI frame 1101 is used to contain undesirable electromagnetic fields from radiating to an external environment. Here the power standoff assembly 300 can either be a separate assembly that is pressed into the frame 1101 or the frame 1101 may become a part of the power standoff assembly's outer cylinder 301 with the inner conductor cylinder 303 and dielectric 302 similar to what has been described in the referenced related patent disclosures. In one embodiment, the outer cylinder 301 protrudes slightly higher than the base of the frame 1101 so as to insure that electrical contact is made at the outer cylinder 301 and not at some general feature of the frame. In this way the integrity of the coaxial current paths are maintained. Note also that in the interest of clarity, FIG. 11A does not show EMI gasketing materials between the frame and PCB 306 and PCB 309.

Sub 7
C17

FIG. 12 illustrates how the power standoff assembly 300 may be used as a circuit element between PCB 306 and PCB 309. The power standoff assembly 300 can be represented electrically as a series RLC circuit as shown. One or more of the circuit elements may be used to enhance the electrical performance of the signals transferred between the two PCBs 306 and 309 by using the power standoff assembly 300 as a filter or as a storage element in the circuit path. The power standoff assembly 300 may be an additional component that is added to either PCB 306 or PCB 309 or it may replace a component on either PCB or both. The benefits may be less complexity overall on either or both PCB's.

Additionally, the capacitive portion of the power standoff assembly 300 may be enhanced by decreasing the dielectric 302 spacing between the inner and outer electrodes and or by choosing a material whose dielectric constant increases the overall capacitance. Thus, the power standoff assembly may also act as an inductive or capacitive storage element.

Conclusion

This concludes the description of the preferred embodiments of the present invention. In summary, the present invention describes a method, apparatus, and article of manufacture for providing power from a first circuit board having a first circuit board first conductive surface and a first circuit board second conductive surface to a second circuit board having a second circuit board first conductive surface and a second circuit board second conductive surface. The apparatus comprises a first conductive member, including a first end having a first conductive member surface electrically coupleable to the first circuit board first conductive surface and a second end distal from the first end having a first conductive member second surface electrically coupleable to the second circuit board first surface. The apparatus also comprises a second conductive member, having a second conductive member first surface electrically coupleable to the first circuit board second surface and a second conductive member second surface distal from the second conductive member first surface electrically coupleable to the second circuit board second conductive surface.

The foregoing description of the preferred embodiment of the invention has been presented for the purposes of illustration and description. It is not intended to be exhaustive or to limit the invention to the precise form disclosed. Many modifications and variations are possible in light of the above teaching. It is intended that the scope of the invention be limited not by this detailed description, but rather by the claims
5 appended hereto. The above specification, examples and data provide a complete description of the manufacture and use of the composition of the invention. Since many embodiments of the invention can be made without departing from the spirit and scope of the invention, the invention resides in the claims hereinafter appended.

01
02
03
04
05
06
07
08
09
10
11
12
13
14
15
16
17
18
19
20
21
22
23
24
25
26
27
28
29
30
31
32
33
34
35
36
37
38
39
40
41
42
43
44
45
46
47
48
49
50
51
52
53
54
55
56
57
58
59
60
61
62
63
64
65
66
67
68
69
70
71
72
73
74
75
76
77
78
79
80
81
82
83
84
85
86
87
88
89
90
91
92
93
94
95
96
97
98
99
100
101
102
103
104
105
106
107
108
109
110
111
112
113
114
115
116
117
118
119
120
121
122
123
124
125
126
127
128
129
130
131
132
133
134
135
136
137
138
139
140
141
142
143
144
145
146
147
148
149
150
151
152
153
154
155
156
157
158
159
160
161
162
163
164
165
166
167
168
169
170
171
172
173
174
175
176
177
178
179
180
181
182
183
184
185
186
187
188
189
190
191
192
193
194
195
196
197
198
199
200
201
202
203
204
205
206
207
208
209
210
211
212
213
214
215
216
217
218
219
220
221
222
223
224
225
226
227
228
229
230
231
232
233
234
235
236
237
238
239
240
241
242
243
244
245
246
247
248
249
250
251
252
253
254
255
256
257
258
259
260
261
262
263
264
265
266
267
268
269
270
271
272
273
274
275
276
277
278
279
280
281
282
283
284
285
286
287
288
289
290
291
292
293
294
295
296
297
298
299
300
301
302
303
304
305
306
307
308
309
310
311
312
313
314
315
316
317
318
319
320
321
322
323
324
325
326
327
328
329
330
331
332
333
334
335
336
337
338
339
340
341
342
343
344
345
346
347
348
349
350
351
352
353
354
355
356
357
358
359
360
361
362
363
364
365
366
367
368
369
370
371
372
373
374
375
376
377
378
379
380
381
382
383
384
385
386
387
388
389
390
391
392
393
394
395
396
397
398
399
400
401
402
403
404
405
406
407
408
409
410
411
412
413
414
415
416
417
418
419
420
421
422
423
424
425
426
427
428
429
430
431
432
433
434
435
436
437
438
439
440
441
442
443
444
445
446
447
448
449
450
451
452
453
454
455
456
457
458
459
460
461
462
463
464
465
466
467
468
469
470
471
472
473
474
475
476
477
478
479
480
481
482
483
484
485
486
487
488
489
490
491
492
493
494
495
496
497
498
499
500
501
502
503
504
505
506
507
508
509
510
511
512
513
514
515
516
517
518
519
520
521
522
523
524
525
526
527
528
529
530
531
532
533
534
535
536
537
538
539
540
541
542
543
544
545
546
547
548
549
550
551
552
553
554
555
556
557
558
559
560
561
562
563
564
565
566
567
568
569
570
571
572
573
574
575
576
577
578
579
580
581
582
583
584
585
586
587
588
589
590
591
592
593
594
595
596
597
598
599
600
601
602
603
604
605
606
607
608
609
610
611
612
613
614
615
616
617
618
619
620
621
622
623
624
625
626
627
628
629
630
631
632
633
634
635
636
637
638
639
640
641
642
643
644
645
646
647
648
649
650
651
652
653
654
655
656
657
658
659
660
661
662
663
664
665
666
667
668
669
670
671
672
673
674
675
676
677
678
679
680
681
682
683
684
685
686
687
688
689
690
691
692
693
694
695
696
697
698
699
700
701
702
703
704
705
706
707
708
709
710
711
712
713
714
715
716
717
718
719
720
721
722
723
724
725
726
727
728
729
730
731
732
733
734
735
736
737
738
739
740
741
742
743
744
745
746
747
748
749
750
751
752
753
754
755
756
757
758
759
760
761
762
763
764
765
766
767
768
769
770
771
772
773
774
775
776
777
778
779
780
781
782
783
784
785
786
787
788
789
790
791
792
793
794
795
796
797
798
799
800
801
802
803
804
805
806
807
808
809
810
811
812
813
814
815
816
817
818
819
820
821
822
823
824
825
826
827
828
829
830
831
832
833
834
835
836
837
838
839
840
841
842
843
844
845
846
847
848
849
850
851
852
853
854
855
856
857
858
859
860
861
862
863
864
865
866
867
868
869
870
871
872
873
874
875
876
877
878
879
880
881
882
883
884
885
886
887
888
889
890
891
892
893
894
895
896
897
898
899
900
901
902
903
904
905
906
907
908
909
910
911
912
913
914
915
916
917
918
919
920
921
922
923
924
925
926
927
928
929
930
931
932
933
934
935
936
937
938
939
940
941
942
943
944
945
946
947
948
949
950
951
952
953
954
955
956
957
958
959
960
961
962
963
964
965
966
967
968
969
970
971
972
973
974
975
976
977
978
979
980
981
982
983
984
985
986
987
988
989
990
991
992
993
994
995
996
997
998
999
1000
1001
1002
1003
1004
1005
1006
1007
1008
1009
1010
1011
1012
1013
1014
1015
1016
1017
1018
1019
1020
1021
1022
1023
1024
1025
1026
1027
1028
1029
1030
1031
1032
1033
1034
1035
1036
1037
1038
1039
1040
1041
1042
1043
1044
1045
1046
1047
1048
1049
1050
1051
1052
1053
1054
1055
1056
1057
1058
1059
1060
1061
1062
1063
1064
1065
1066
1067
1068
1069
1070
1071
1072
1073
1074
1075
1076
1077
1078
1079
1080
1081
1082
1083
1084
1085
1086
1087
1088
1089
1090
1091
1092
1093
1094
1095
1096
1097
1098
1099
1100
1101
1102
1103
1104
1105
1106
1107
1108
1109
1110
1111
1112
1113
1114
1115
1116
1117
1118
1119
1120
1121
1122
1123
1124
1125
1126
1127
1128
1129
1130
1131
1132
1133
1134
1135
1136
1137
1138
1139
1140
1141
1142
1143
1144
1145
1146
1147
1148
1149
1150
1151
1152
1153
1154
1155
1156
1157
1158
1159
1160
1161
1162
1163
1164
1165
1166
1167
1168
1169
1170
1171
1172
1173
1174
1175
1176
1177
1178
1179
1180
1181
1182
1183
1184
1185
1186
1187
1188
1189
1190
1191
1192
1193
1194
1195
1196
1197
1198
1199
1200
1201
1202
1203
1204
1205
1206
1207
1208
1209
1210
1211
1212
1213
1214
1215
1216
1217
1218
1219
1220
1221
1222
1223
1224
1225
1226
1227
1228
1229
1230
1231
1232
1233
1234
1235
1236
1237
1238
1239
1240
1241
1242
1243
1244
1245
1246
1247
1248
1249
1250
1251
1252
1253
1254
1255
1256
1257
1258
1259
1260
1261
1262
1263
1264
1265
1266
1267
1268
1269
1270
1271
1272
1273
1274
1275
1276
1277
1278
1279
1280
1281
1282
1283
1284
1285
1286
1287
1288
1289
1290
1291
1292
1293
1294
1295
1296
1297
1298
1299
1300
1301
1302
1303
1304
1305
1306
1307
1308
1309
1310
1311
1312
1313
1314
1315
1316
1317
1318
1319
1320
1321
1322
1323
1324
1325
1326
1327
1328
1329
1330
1331
1332
1333
1334
1335
1336
1337
1338
1339
1340
1341
1342
1343
1344
1345
1346
1347
1348
1349
1350
1351
1352
1353
1354
1355
1356
1357
1358
1359
1360
1361
1362
1363
1364
1365
1366
1367
1368
1369
1370
1371
1372
1373
1374
1375
1376
1377
1378
1379
1380
1381
1382
1383
1384
1385
1386
1387
1388
1389
1390
1391
1392
1393
1394
1395
1396
1397
1398
1399
1400
1401
1402
1403
1404
1405
1406
1407
1408
1409
1410
1411
1412
1413
1414
1415
1416
1417
1418
1419
1420
1421
1422
1423
1424
1425
1426
1427
1428
1429
1430
1431
1432
1433
1434
1435
1436
1437
1438
1439
1440
1441
1442
1443
1444
1445
1446
1447
1448
1449
1450
1451
1452
1453
1454
1455
1456
1457
1458
1459
1460
1461
1462
1463
1464
1465
1466
1467
1468
1469
1470
1471
1472
1473
1474
1475
1476
1477
1478
1479
1480
1481
1482
1483
1484
1485
1486
1487
1488
1489
1490
1491
1492
1493
1494
1495
1496
1497
1498
1499
1500
1501
1502
1503
1504
1505
1506
1507
1508
1509
1510
1511
1512
1513
1514
1515
1516
1517
1518
1519
1520
1521
1522
1523
1524
1525
1526
1527
1528
1529
1530
1531
1532
1533
1534
1535
1536
1537
1538
1539
1540
1541
1542
1543
1544
1545
1546
1547
1548
1549
1550
1551
1552
1553
1554
1555
1556
1557
1558
1559
1560
1561
1562
1563
1564
1565
1566
1567
1568
1569
1570
1571
1572
1573
1574
1575
1576
1577
1578
1579
1580
1581
1582
1583
1584
1585
1586
1587
1588
1589
1590
1591
1592
1593
1594
1595
1596
1597
1598
1599
1600
1601
1602
1603
1604
1605
1606
1607
1608
1609
1610
1611
1612
1613
1614
1615
1616
1617
1618
1619
1620
1621
1622
1623
1624
1625
1626
1627
1628
1629
1630
1631
1632
1633
1634
1635
1636
1637
1638
1639
1640
1641
1642
1643
1644
1645
1646
1647
1648
1649
1650
1651
1652
1653
1654
1655
1656
1657
1658
1659
1660
1661
1662
1663
1664
1665
1666
1667
1668
1669
1670
1671
1672
1673
1674
1675
1676
1677
1678
1679
1680
1681
1682
1683
1684
1685
1686
1687
1688
1689
1690
1691
1692
1693
1694
1695
1696
1697
1698
1699
1700
1701
1702
1703
1704
1705
1706
1707
1708
1709
1710
1711
1712
1713
1714
1715
1716
1717
1718
1719
1720
1721
1722
1723
1724
1725
1726
1727
1728
1729
1730
1731
1732
1733
1734
1735
1736
1737
1738
1739
1740
1741
1742
1743
1744
1745
1746
1747
1748
1749
1750
1751
1752
1753
1754
1755
1756
1757
1758
1759
1760
1761
1762
1763
1764
1765
1766
1767
1768
1769
1770
1771
1772
1773
1774
1775
1776
1777
1778
1779
1780
1781
1782
1783
1784
1785
1786
1787
1788
1789
1790
1791
1792
1793
1794
1795
1796
1797
1798
1799
1800
1801
1802
1803
1804
1805
1806
1807
1808
1809
1810
1811
1812
1813
1814
1815
1816
1817
1818
1819
1820
1821
1822
1823
1824
1825
1826
1827
1828
1829
1830
1831
1832
1833
1834
1835
1836
1837
1838
1839
1840
1841
1842
1843
1844
1845
1846
1847
1848
1849
1850
1851
1852
1853
1854
1855
1856
1857
1858
1859
1860
1861
1862
1863
1864
1865
1866
1867
1868
1869
1870
1871
1872
1873
1874
1875
1876
1877
1878
1879
1880
1881
1882
1883
1884
1885
1886
1887
1888
1889
1890
1891
1892
1893
1894
1895
1896
1897
1898
1899
1900
1901
1902
1903
1904
1905
1906
1907
1908
1909
1910
1911
1912
1913
1914
1915
1916
1917
1918
1919
1920
1921
1922
1923
1924
1925
1926
1927
1928
1929
1930
1931
1932
1933
1934
1935
1936
1937
1938
1939
1940
1941
1942
1943
1944
1945
1946
1947
1948
1949
1950
1951
1952
1953
1954
1955
1956
1957
1958
1959
1960
1961
1962
1963
1964
1965
1966
1967
1968
1969
1970
1971
1972
1973
1974
1975
1976
1977
1978
1979
1980
1981
1982
1983
1984
1985
1986
1987
1988
1989
1990
1991
1992
1993
1994
1995
1996
1997
1998
1999
2000
2001
2002
2003
2004
2005
2006
2007
2008
2009
2010
2011
2012
2013
2014
2015
2016
2017
2018
2019
2020
2021
2022
2023
2024
2025
2026
2027
2028
2029
2030
2031
2032
2033
2034
2035
2036
2037
2038
2039
2040
2041
2042
2043
2044
2045
2046
2047
2048
2049
2050
2051
2052
2053
2054
2055
2056
2057
2058
2059
2060
2061
2062
2063
2064
2065
2066
2067
2068
2069
2070
2071
2072
2073
2074
2075
2076
2077
2078
2079
2080
2081
2082
2083
2084
2085
2086
2087
2088
2089
2090
2091
2092
2093
2094
2095
2096
2097
2098
2099
2100
2101
2102
2103
2104
2105
2106
2107
2108
2109
2110
2111
2112
2113
2114
2115
2116
2117
2118
2119
2120
2121
2122
2123
2124
2125
2126
2127
2128
2129
2130
2131
2132
2133
2134
2135
2136
2137
2138
2139
2140
2141
2142
2143
2144
2145
2146
2147
2148
2149
2150
2151
2152
2153
2154
2155
2156
2157
2158
2159
2160
2161
2162
2163
2164
2165
2166
2167
2168
2169
2170
2171
2172
2173
2174
2175
2176
2177
2178
2179
2180
2181
2182
2183
2184
2185
2186
2187
2188
2189
2190
2191
2192
2193
2194
2195
2196
2197
2198
2199
2200
2201
2202
2203
2204
2205
2206
2207
2208
2209
2